Upgrade Brother QL-1050 and QL-1060N Print Driver

Purpose

To be able to use the new label **DK-22246** clients need to upgrade the print drivers.

Instructions Search for the correct printer -<u>https://support.brother.com/g/b/productsearch.aspx?c=us&lang=en&content=dl</u> Steps below are more or less identical on both QL-1050 and QL-1060N

- 1. If you have QL-1060N, download the driver from
 - <u>https://support.brother.com/g/b/downloadtop.aspx?c=gb&lang=en&prod=ql</u> <u>1060neuk</u> and select your Operating System. or
 - o <u>https://sstmvc.com/clientsetup/ql1060.exe</u>
 - for clients running Windows 10 x64

Support & Downloads	ol-1060N Downloads		
	Select Your Operating System (OS) STEP 1: Select OS Family		
	● Windows ○ Mac ○ Linu	Х	
Martin	STEP 2: Select OS Version		
Not your product?	O Windows 10 (32-bit)	O Windows 2000	
ownloads O	Windows 10 (64-bit)	O Windows Server 2016	
AQo & Traublachasting	O Windows 8 (32-bit)	O Windows Server 2012 R2	
Acts & Incubieshooting	O Windows 8 (64-bit)	O Windows Server 2012	
anuals O	O Windows 7 (32-bit)	O Windows Server 2008 R2	
Consumables & Accessories 🛛 🔘	O Windows 7 (64-bit)	O Windows Server 2008 (32-bit)	
upported OS O	O Windows Vista (32-bit)	O Windows Server 2008 (64-bit)	
necification	O Windows Vista (64-bit)	O Windows Server 2003	
specification •	O Windows XP Home/Professional		
United Kingdom(English)	How to identify your Operating System	em (OS) Search	
Change Countries or Region			
(Language)	Information	What's New?	
	For Windows 10 Users : Click here for information on downloading files. Windows 8.1 Information:	 11/03/2019 P-touch Editor5 x 10 / 10x84 / 8 / 8x84 / 7 / 7x84 / Server 2016. Server 2012 R2 / Server 2012 / Server 2008 R2 / Server 2008 / Server 2008 84 	

- 2. Unpack to your preferred location.
- 3. Disconnect the Printer from your Computer
- 4. Go to the location you have unpacked the files and run D_SETUP, preferable run as administrator.
- 5. You will be notified to disconnect the printer and if you have done so click Start.

 \times

Brother QL-1060N Driver will be installed.



6. Make sure Local Printer with USB cable is selected and click Next Brother Printer Driver Installation

Select Connection	124
Select the appropriate connection method. • Local Printer with USB cable The printer is connected directly to this PC using a USB	cable.
O Brother Peer-to-Peer Network Printer Print directly to the printer over the network.	
O Network Shared Printer All Jobs are sent to queue on a central server.	
< Back Next	> Cancel

Printer Driver Installer - Insta	IIShield Wizard		\times
Se Driver Setup (Brother (QL-1060N)	×	
	Install the printer.		
	Connect Brother QL-1060N, and then turn it on.		
Install	< Back Next > Cance	l ancel	

7. You will then be requested to connect the printer and then turn it on. Do so.

8. If requested to restart your computer Click **OK** in order to enable the new driver.

Printer Driver	Installer - InstallShield Wizard	>	<
Setup Stat	tus	. Aller	
	🐻 Brother QL-1060N Update Utility	×	
Brother QI	Brother QL-1060N is version V1.300 .		
Now Copy	In order to enable the new driver, restart the computer.		
	Yes, I want to restart my computer now.		
	O No, I will restart my computer later.		
	OK		
install5hield —		Cancel	

- 9. When the computer is restarted go to control panel and open **Devices and Printers**
- 10. Right click QL-1060N printer and select **Printer properties**.
- 11. Click **Advanced Tab** then, **Printing Defaults** button. If the button is greyed out you will need to login the system with an account with administrator privileges.

🖶 Egenskaper for Brother QL-1060N

Generelt Deling Porter Avansert Fargebehandling Sikkerhet Enhetsinnstillinger
 Alltid tilgjengelig Tilgjengelig fra 00:00 til 00:00
Prioritet: 1
Driver: Brother QL-1060N \sim Ny driver
Egg utskriftsdokumenter i kø slik at programmet skriver ut raskere.
🔘 Start utskriften etter at siste side er i utskriftskøen.
Begynn utskrift umiddelbart.
O Skriv direkte til skriveren.
🗌 Hold tilbake dokumenter som ikke samsvarer
🗹 Skriv ut dokumenter i skriverkøen først
Behold utskrevne dokumenter
🗹 Aktiver avanserte utskriftsfunksjoner
Utskriftsstandarder Utskriftsprosessor Skilleside
OK Avbryt Bruk

12. On the Brother QL-1060N properties, make sure "Edipost-etikett (103x192mm)" is selected on the Format dropdown and then Click on **Label format definitions** button below. If this format is not available on the drop down list, do as follow: Click on 'Def for Etikettformat', to make a new one. Follow the yellow fields below, from top to down.

🖶 Utskriftsinnstillinger fo	or Brother QL-1060N	\times
Papir Grafikk Alternativ	Def. for etikettformat ? ×	
	Navn: Edipost-etikett 🗸	
	Importere Eksportere	
*	Teipens 103mm V	
^{164mm} A	Lengde: [192 mm] Kin: 25 - Maks: 3000	
↓] ←] 104mm	Mate: Min: 3 - Maks: 127	
	192mm	
	Lagre Slett	
	CK Avbryt Standard	
	Def. for etikettformat Standard	
	OK Avbryt Bruk	

13. Choose the new format "Edipost-etikett" then click **Save**.

🖶 Utskriftsinnstillinger for B	rother QL-1060N		>
Papir Grafikk Alternativ S	Støtte		
	Format:	Edipost-etikett ~	
	Teipens bredde:	103mm ~	
192mm A	Lengde:	Min: 25 Maks: 3000	
	Mate:	Min: 3 Maks: 127 4 mm < >	
	Retning:	◯ Liggende	
		● Stående	
	Eksemplarer:	1 Sorter	
		Omvendt rekkefølge	
	Kvalitet:	 Gi prioritet til utskriftshastighet 	
		◯ Gi prioritet til utskriftsk∨alitet	
	Start utskrift:	Begynn utskriften umiddelbart	
		◯ Etter at én side er mottatt	
		Def. for etikettformat Standard	
		OK Avbryt Bruk	

- 14. Click **OK**, if user access list prompts you to allow changes click **Yes**.
- 15. Make sure that format Edipost-etikett (103x192mm) is selected and the width is set to 103mm.
- 16. Click **OK**
- 17. Click General Tab

	Citil and an	Endersteinen ditter eine
gebenandling	Sikkerhet	Enhetsinnstillinger
Tilgjengeli	ge papirty;	per:
Tilgjengeli	ge papirty;	ber:
Tilgjengeli	ge papirty;	oer:
Tilgjengeli	ge papirty;	per:
	rgebehandling	rgebehandling Sikkerhet

18. Click Properties

19. Make sure that format Edipost-etikett (103x192mm) is selected and the width is set to <mark>103mm</mark>.

OK

Avbryt Bruk

Utskriftsinnstillinger for	Brother QL-1060N		×
Papir Grafikk Alternativ	Støtte		
	Format:	Edipost-etikett ~	
192mm	Teipens bredde: Lengde: Mate:	103mm Min: 25 - Maks: 3000 192 mm Min: 3 - Maks: 127 4	
	Retning:	◯ Liggende ● Stående	
	Eksemplarer:	1 Sorter	
	Kvalitet:	 Gi prioritet til utskriftshastighet Gi prioritet til utskriftskvalitet 	
	Start utskrift:	 Begynn utskriften umiddelbart Etter at én side er mottatt 	
		Def. for etikettformat Standard	
		OK Avbryt Bruk	

- 20. Click **OK.**
- 21. Upgrade completed.
- 22. Test print outs.